

Datenblatt der Serie AX, Stanzung für Postschloss, Video, 2-reihig AX20XXP1VI

Toleranz der UP-Dose: $\pm 2\text{mm}$

ARTIKEL NR.	ABMESSUNGEN FRONTPLETTE BxHxT in mm	ABMESSUNGEN UP-DOSE BxHxT in mm	ANORDNUNG
-------------	---	---------------------------------------	-----------

AX2002P1VI	180 x 270 x 2,5	160 x 250 x 55	1-1 Tasten + Videokamera Fermax Marine
AX2004P1VI	180 x 293 x 2,5	160 x 275 x 55	2-2 Tasten + Videokamera Fermax Marine
AX2006P1VI	180 x 316 x 2,5	160 x 298 x 55	3-3 Tasten + Videokamera Fermax Marine
AX2008P1VI	180 x 339 x 2,5	160 x 321 x 55	4-4 Tasten + Videokamera Fermax Marine
AX2010P1VI	180 x 362 x 2,5	160 x 344 x 55	5-5 Tasten + Videokamera Fermax Marine
AX2012P1VI	180 x 385 x 2,5	160 x 367 x 55	6-6 Tasten + Videokamera Fermax Marine
AX2014P1VI	180 x 408 x 2,5	160 x 390 x 55	7-7 Tasten + Videokamera Fermax Marine
AX2016P1VI	180 x 431 x 2,5	160 x 413 x 55	8-8 Tasten + Videokamera Fermax Marine
AX2018P1VI	180 x 454 x 2,5	160 x 436 x 55	9-9 Tasten + Videokamera Fermax Marine
AX2020P1VI	180 x 477 x 2,5	160 x 459 x 55	10-10 Tasten + Videokamera Fermax Marine
AX2022P1VI	180 x 500 x 2,5	160 x 482 x 55	11-11 Tasten + Videokamera Fermax Marine
AX2024P1VI	180 x 523 x 2,5	160 x 503 x 55	12-12 Tasten + Videokamera Fermax Marine