

Datenblatt der Serie AX, Video, 4-reihig AX40XXVI

Toleranz der UP-Dose: $\pm 2\text{mm}$

ARTIKEL NR.	ABMESSUNGEN FRONTPLETTE BxHxT in mm	ABMESSUNGEN UP-DOSE BxHxT in mm	ANORDNUNG
AX4028VI	340 x 362 x 2,5	320 x 342 x 55	7-7-7-7 Tasten + VIDEO FERMAX
AX4032VI	340 x 385 x 2,5	320 x 365 x 55	8-8-8-8 Tasten + VIDEO FERMAX
AX4036VI	340 x 408 x 2,5	320 x 388 x 55	9-9-9-9 Tasten + VIDEO FERMAX
AX4040VI	340 x 431 x 2,5	320 x 411 x 55	10-10-10-10 Tasten + VIDEO FERMAX
AX4044VI	340 x 454 x 2,5	320 x 434 x 55	11-11-11-11 Tasten + VIDEO FERMAX
AX4048VI	340 x 477 x 2,5	320 x 457 x 55	12-12-12-12 Tasten + VIDEO FERMAX
AX4052VI	340 x 500 x 2,5	320 x 480 x 55	13-13-13-13 Tasten + VIDEO FERMAX
AX4056VI	340 x 523 x 2,5	320 x 503 x 55	14-14-14-14 Tasten + VIDEO FERMAX
AX4060VI	340 x 546 x 2,5	320 x 526 x 55	15-15-15-15 Tasten + VIDEO FERMAX